



# RS-12

## ROTARY SWITCH BOX

USERS GUIDE

COMCODE: 407 686 732

PEC CODE: 8809-022

---



**General**

The RS-12 rotary switch connects 1 of 12 Tip & Ring pairs to a single T & R output. This output may be used for recording. A 12 position switch selects 1 of the 12 pairs.

None of the 12 pairs are terminated. Connecting to the output of the RS-12 only terminates the selected pair.

**Connections**

- 1] The input cable is 2.5ft. long, with a 25-pair male amphenol plug.
- 2] The selected pair is output on a mini-phone jack located on the front of the RS-12.
- 3] Pair 25 on the input cable is common to the mini-phone jack, and may also be used for the output.

**Specifications**

**General**

**SIZE (overall):** .....3.125"H x 3.15"W x 4.75"D

**WEIGHT:** .....1.4 lbs.

**Accessories supplied**

**1ea. MA1 cable** - 3ft length. 1/8" mini-phone plug to 1/8" mini-phone plug.

Specifications subject to change without notice.

<b>PIN</b>	<b>PAIR</b>	<b>SWITCH</b>	<b>OUTPUT</b>
26 1	1	1	OUTPUT OF SELECTED PAIR CONNECTS TO MINI-PHONE JACK.
27 2	2	2	
28 3	3	3	
29 4	4	4	
30 5	5	5	
31 6	6	6	
32 7	7	7	
33 8	8	8	
34 9	9	9	
35 10	10	10	
36 11	11	11	
37 12	12	12	
38-49 13-24	not used		
50 25	25	1 thru 12	COMMON TO MINI- PHONE JACK.



**Starcom Incorporated**

3303 North Dixie Highway  
Boca Raton, FL. 33431

phone: (561) 392-7001 ★ fax: (561) 392-7003 ★ email: [info@starcom-inc.com](mailto:info@starcom-inc.com) ★ internet: [www.starcom-inc.com](http://www.starcom-inc.com)